

FAIRCHILD DIODES

DIODES

MONOLITHIC DIODE ARRAYS (NUMERIC LISTING) (Cont'd) PLASTIC - CERAMIC - METAL PACKAGES

Item	DEVICE NO.	BV V Min	V _F V Max	@	I _F mA	ΔV _F mV Max	t _{rr} ns Min	Configuration	Package No.
1	FSA2503M	60	1.0		100	15	10	2M8	TO-116
2	FSA2503P	60	1.0		100	15	10	2M8	TO-116
3	FSA2504M	60	1.0		100	15	10	2M8	TO-86
4	FSA2508M	60	1.3		500	15	10	4M4	6B
5	FSA2508P	60	1.3		500	15	10	4M4	9B
6	FSA2509M	60	1.3		500	15	10	2M8	TO-116
7	FSA2509P	60	1.3		500	15	10	2M8	TO-116
8	FSA2510M	60	1.3		500	15	10	M16	TO-116
9	FSA2510P	60	1.3		500	15	10	M16	TO-116
10	FSA2563M	60	1.3		500	15	10	CC8	TO-116
11	FSA2563P	60	1.3		500	15	10	CC8	TO-116
12	FSA2564M	60	1.3		500	15	10	CA8	TO-116
13	FSA2564P	60	1.3		500	15	10	CA8	TO-116
14	FSA2565M	60	1.3		500	15	10	CC13	TO-116
15	FSA2565P	60	1.3		500	15	10	CC13	TO-116
16	FSA2566M	60	1.3		500	15	10	CA13	TO-116
17	FSA2566P	60	1.3		500	15	10	CA13	TO-116
18	FSA2619M	100	1.0		10	15	5	S8	6B
19	FSA2619P	100	1.0		10	15	5	S8	9B
20	FSA2620M	100	1.0		10	15	5	S7	TO-116
21	FSA2620P	100	1.0		10	15	5	S7	TO-116
22	FSA2621M	100	1.0		10	15	5	S7	TO-86
23	FSA2702M	60	1.0		200	3	6	R4	TO-33
24	FSA2703M	60	1.0		200	3	6	R4	TO-72
25	FSA2704M	60	1.0		200	—	6	R4	TO-33
26	FSA2705M	60	1.0		200	—	6	R4	TO-72
27	FSA2719M	75	1.0		10	15	6	S8	6B
28	FSA2719P	75	1.0		10	15	6	S8	9B
29	FSA2720M	75	1.0		10	15	6	S7	TO-116
30	FSA2720P	75	1.0		10	15	6	S7	TO-116
31	FSA2721	75	1.0		10	15	6	S7	TO-86

Note: See configurations on following page.

2

10732 50144

McGraw-Hill

Sevenoaks

1211111